


# BENDING GUIDE

# SOLUTIONS FOR POORLY BENT TUBES

### 1st BEND DIE

Hardened tool steel or alloy steel, heat—treated and nitride. The drive key must be parallel to the clamp insert. The bore should have a slip fit over the centering ring or spindle.

NOTE: Bend dies may have special tube grooves with captive lip or heart shaped.



#### 2nd CLAMP DIE

Hardened tool steel or alloy steel, heat-treated and nitride. Preferable length is 3-1/2" TOD. The tube groove is grit blasted or may be serrated if it is less than the preferred length.

2


With the tube held in the bend die. advance the clamp die and adjust it for vertical alignment. Adjust for parallel contact with the entire length of the clamp. Adjust for pressure.

## 3rd PRESSURE DIE

Alloy steel and nitride. The tube groove must be parallel to the back of the die. If a static pressure die system is used, the length equals 3-1/2" TOD; if a follower type is used, the length equals 180'+2 TOD. If a boosted system is used, the groove should be grit blasted.


To set-up; With the tube clamped to the bend die, advance the pressure die and adjust it for vertical alignment. Adjust it for minimum pressure and increase as required in small increments.

nolder. Unclamp the pressure and clamp dies, the tip of the wiper should be very close to tangent. Adjust for rake and vertical alianment. Lubricate each tube





#### 4th MANDREL

Chrome plated, heat-treated Steel or Bronze. Use Chrome plated mandrel when bending ferrous material such as Brass, Copper, etc. Use Bronze for non-ferrous material such as Stainless Steel, Titanium, etc. The mandrel fits inside the tube and supports the wall to prevent flattening during the bending process.



Start with a clean, débur and lubricated tube with elongation properties sufficient to produce the bend.







After the initial tooling set-up has been made, make a sample bend to determine what tools to adjust in order to make a better bend. It is important to keep in

mind the basic principle that material is stretched on the outside of the bend and compressed on the inside of the bend. Make one adjustment for each trial bend unless the second adjustment is very obviously needed. Avoid the tendency to first increase pressure die force rather than adjust the wiper die or mandrel location.

NOTE: There are certainly other solutions that could be made for the following problems. These illustrations are a few examples of how to read a bend and improve







bend and even extending into the

wiper may be worn out-have it

wiper die greg.

the tooling set-up.





PROBLEM: Heavy wrinkles through the bend area only and linear scratches in the grip area which indicates clamp

SOLUTION: A)Reduce the pressure die force. B)Check the location (and lube) of the mandrel and wiper die. C)Increase pressure on the clamp die. D)Use serrated or carbide spray in the tube aroove of the clamp die.



14955 East Salt Lake Avenue, City of Industry, California 91746 Phone: 626-968-9686 Fax: 626-333-3610